


BBAtechniek

specialist in camper- en caravanaccessoires

Dolphin

charger



	12V					24V
	10A	15A	25A	40A	60A	20A
Input						
Input Voltage	230V (+/- 15%) 115V available on request		115V / 230V (+/- 15%) Automatic Switchover			
Frequency	50Hz/60Hz (+/-10%)					
Cos	0.6 typ		0.9 typ			
Efficiency	80% typ					
Max. Current 115V/230V	NA/1,3A	NA/1,9A	4A/2A	7A/3,5A	12A/6A	7A/3,5A
Fuse (5x20mm)	T2A 250V	T3,15A 250V	T6A 250V	T10A 250V	T16A 250V	T10A 250V
Output						
Number of outputs	3 isolated outputs					
Number of charging curves	4 programs, position selected by dip switch NEW - one of which is LiFeSO4 with integrated BMS					
Charging curve	IUUo + weekly automatic equalisation					
Weekly equalisation	Automatic					
Voltage share	+/-2%					
Ripple	< 1% pp (BW < 20MHz)					
Fuse (automatic mini)	F15A 32V	F20A 32V	2 x F15A 32V	2x F25A 32V	3X F25A 32V	2 x F15A 32V
Protection						
	In case of output overload, Excessive internal temperature Charging voltage too high, Reverse battery polarity (fuse)					
General						
Display	Tricolour LED					
Night/Silent Mode	By button					
Operating temperature	-10°C to +50°C					
Storage temperature	-20°C to +70°C					
Humidity	10% to 90% (without condensation)					
Ventilation	Natural		Forced fan cooling			
Security	EN60335-2-29 (2002)					
Housing	Powder coating aluminium					
Mouting	2 screws 4mm				4 screws 4mm	2 screws 4mm
Dimensions	96 x 120 x 238 mm		96 x 120 x 354 mm		274 x 240 x 107 mm	96 x 120 x 354 mm
Weight	1,30 Kg		1,90 Kg		3 Kg	1,90 Kg
Input terminals	20A 230V, 4mm² max WINSTA - WAGO 770.813 / G11-000				4 Poles 35mm², 125amp max clamp terminals	20A 230V, 4mm² max WINSTA - WAGO 770.813 / G11-000
Battery terminal	40A 630V, 10mm² max PHOENIX CONTACT PC6-16/4-G1F,16					
CAN BUS	No				Yes	No